

JAY 10

10ℓ Oxygen Concentrator




LOW OXYGEN PURITY

The indicator will turn red when the oxygen purity is less than 82%



HIGH TEMPERATURE

When the internal temperature of the machine exceeds 50°C, the indicator will turn red and an audible alarm will sound



HIGH/LOW PRESSURE

When the machine running pressure is too high, the indicator light will turn red, or yellow when the running pressure is too low. The audible alarm will sound



POWER FAILURE

The indicator light will turn red when there is no power to the machine.



JAY-10

JAY-10			
Flow Rate	0.05--10L/min	Weight	27Kgs
Oxygen Concentration	93% (±3%)	Power Consumption	≤ 880W
Outlet Pressure	6-10 psi (0.04-0.07 Mpa)	Input Frequency	50/60 Hz
Sound Level	≤ 50db	Input Voltage	AC 230V/110V ± 10%
Alarm	Power failure; high and low pressure; No flow; Low O2 Concentration		
OPI Alarm	Audible and Visual alarm at low oxygen concentration (<82%)		

PRODUCT DETAILS

Good details make good products

